# LCP-102
Multifunction Remote Assignment Panel

Features

The LCP-102 combines the features of an Analog Trim Panel, a Camera Delegate Panel, and a Program Assign Panel in a single frame that is only two rack units high. You can easily switch between its three panel modes and make rapid configuration changes using the menu selector on the front panel. In each mode, you can make up to 64 assignments and then adjust the levels for those assignments. For example, in TRIMS mode, you can assign and adjust the analog input and output trims for up to 64 intercom ports. In PAP mode, you can select the program input source and set its level for each of 64 IFB's. In CDP mode, you can assign up to 64 intercom ports to any combination of party lines and then adjust the listen level for each participant on that party line.

The LCP-102 connects to the auxiliary data port of any ADAM, ADAM CS, or Zeus Intercom System, and it also has a loop connector for connection to another auxiliary device, such as another LCP-102, or a UIO-256 Universal Input/Output frame. Since a single LCP-102 provides trim adjustments for 64 ports, only one unit is required to completely configure an ADAM CS or Zeus system. For larger ADAM Intercom Systems, up to 15 additional LCP-102 frames can be connected via the loop connectors.

Line Drawing

LCP-102 Specifications

Dimensions
2 RU DEEP (7"), 19" WIDE, 7" L

Weight
8.20 LBS

Power Consumption
13 WATTS

Data Connector
DB-9 MALE
PIN 1 – COMMON
PIN 2 – DATA –
PIN 3 – N/A
PIN 4 – N/A
PIN 5 – N/A
PIN 6 – N/A
PIN 7 – DATA +
PIN 8 – N/A
PIN 9 – N/A

Loop Connector
DB-9 FEMALE
PIN 1 – COMMON
PIN 2 – DATA –
PIN 3 – N/A
PIN 4 – N/A
PIN 5 – N/A
PIN 6 – N/A
PIN 7 – DATA +
PIN 8 – N/A
PIN 9 – N/A

Ordering Information
LCP-102
Multifunction Remote Assignment Panel
Catalog Number: 90007486001